

## QUICK GUIDE

### ACCESS THE INTERNET

To access the Internet, do as follows:

1. Connect the LAN cable between your computer and the EXPLORER 325 terminal.
2. Start up your computer.
3. Open your browser.

If your data connection is automatically enabled, you should now have access to the Internet.

If not, you must start a connection as described in the next section.

### START/STOP DATA SESSIONS ON LAN

You can start and stop data sessions with a connected Thrane IP Handset (with the local number 0501, master handset), or with the terminal's built-in web interface.

**THRANE IP HANDSET:** To start or stop data sessions with the IP Handset, do as follows:

1. From the BGAN menu, select **Connect**.
2. Use the left/right keys to find the network user group for the application you want to start or stop.
3. Use the up/down keys to select the connection you wish to start (Active) or stop (Inactive).
4. Press **Start** to start a connection, or press **Stop** to stop the connection.



**NOTE:** When running a Streaming session you are charged for the time you are connected. A started Streaming session will stay active until you stop it.

**WEB INTERFACE:** Using a connected computer you can also start or stop data sessions from the Dashboard of the terminal's built-in web interface.

To access the web interface, open your browser and enter the IP address of your EXPLORER 325. The default IP address is **192.168.0.1**.

Note that Streaming profiles must first be defined and activated in the LAN window of the web interface.

For further information, refer to the EXPLORER 325 User Manual.

## **MAKE A VOICE CALL**

To make a call from your EXPLORER 325 terminal, dial

**00 <country code> <phone number> #**

Example: Thrane & Thrane A/S in Denmark:  
**00 45 39558800 #**

To make a call **to** the terminal, dial  
**+870 <mobile number>**

If the mobile number is listed in the web interface, you can look it up by selecting **PHONE BOOK > Mobile numbers**.

If the number is not listed, refer to your airtime subscription. We recommend using the web interface to save the mobile number for future reference. See the User Manual for details.

## **MAKE A LOCAL CALL**

You can make local calls between phones connected to the same terminal.

To make a local call to an IP handset, dial the number of the IP handset (e.g. **0501**) followed by **#**.

To make a local call to an analog phone, dial **0301** followed by **#**.

For information on allocation of local numbers, refer to the EXPLORER 325 User Manual.

## **SEND A FAX**

To send a fax from the Phone interface of the terminal, dial

**2\* 00 <country code> <phone number> #**

Example: Thrane & Thrane A/S in Denmark:  
**2\* 00 45 39558888 #**

"2\*" forces the connection to use 3.1 kHz Audio. The connection uses Standard Audio by default.

To send a fax **to** the terminal, dial  
**+870 <3.1 kHz Audio mobile number>**

Alternatively you can send a fax directly from your browser, using a "web fax" feature provided by an electronic fax provider.